



### Features:

- ❖ Zone selection button: User can choose single zone, multi zones, or all zones for paging.
- ❖ Call button and warning tone button: Press call button when the warning tone button is on, the ring come out firstly.
- ❖ Auto standby function: When no signal is detected from mic for one minute, the conversation will close automatically. And the call button is off.
- ❖ RS485 online port, can be cascaded to 6 pieces.

### Specifications:

Model	IT-ZPA6
Mic Type	Condenser Microphone

\*Picture for illustration purpose only



Polar Pattern	Cardioid
Capacity	6 Zone
Output level	1V/600Ω
Sensitivity	2.6mV/Pa
Frequency response	20-20KHz
THD	≤1%
Communication Distance	1KM
Power Supply	24-48V
Temperature	0°-55° C
Humidity	10%-90%

\*Picture for illustration purpose only